



## GUIDELINES ON TRANSMISSION TARIFICATION

### EREGG Proposal

2 May 2005

### EXPLANATORY NOTE

#### Background

Article 8(3) of the Regulation on Cross Border Electricity exchanges<sup>1</sup> provides for guidelines to be adopted to “determine appropriate rules leading to a progressive harmonisation of the underlying principles for the setting of charges applied to producers and consumers (load) under national tariff systems, including the reflection of the inter-TSO compensation mechanism in national network charges and the provision of appropriate and efficient locational signals, in accordance with the principles set out in Article 4.”

Article 4 itself discusses the requirements relating to transmission tariffs. In particular, Article 4(2) states that;

Where appropriate, the level of the tariffs applied to producers and/or consumers shall provide locational signals at European level, and take into account the amount of network losses and congestion caused, and investment costs for infrastructure.

Meanwhile Article 4(4) requires that

Providing that appropriate and efficient locational signals are in place, in accordance with paragraph 2, charges for access to networks applied to producers and consumers shall be applied regardless of the countries of destination and, origin, respectively, of the electricity, as specified in the underlying commercial arrangement.

The attached guidelines therefore fulfil these requirements of the Regulation.

#### 1. CURRENT SITUATION,

Transmission tariffs in Member States already reflect most of the requirements of the Regulation in that they are, by and large “entry-exit” tariff systems rather than being distance based. The main component of tariffs is related to the costs that are considered fixed in the short run. These charges may be imposed on generators, called the ‘G’ charge, and those for the load, called the ‘L’ charge. The allocation of these charges in all Member States fulfils the criteria that the majority of the charges fall on load rather than generation and in some Member States the ‘G’ charge is zero.

Deleted: POSITION

Deleted: those

Deleted: fixed

Deleted: of

Deleted: network

Deleted: for access to networks”.  
These

Deleted: cases

<sup>1</sup> Regulation 1228/03/EC

As well as the fixed costs of the transmission network in the short run, ie capital and operation costs, transmission tariffs often include specific charges for losses, congestion and other ancillary services.

Generators and consumers may also be required to pay a one-off charge for their initial connection to the grid, usually called "connection charge". Charges related to losses, congestion and other ancillary services are also an important feature. These charges are not, however, considered to be part of the G charge for the purpose of these Guidelines.

There remain differences in the level of transmission charges, and the split between G and L charges between Member States. The structures of the tariffs are also different. In case of several transmission grids within one Member State, transmission tariffs could be different within the different transmission system operators.

Finally, charges relating to underlying commercial arrangements have been removed from January 2004 in Member States participating in the inter-TSO compensation mechanism.

- Deleted: .
- Deleted: also usually
- Deleted:
- Deleted: loss
- Deleted:
- Inserted:
- Deleted: customers
- Deleted: .
- Deleted: congestion
- Deleted: of tariffication.
- Deleted: significant
- Deleted: one
- Deleted: State and another.
- Deleted: revised
- Deleted: However some border charges remain for those Member States which do not yet participate in this mechanism.

## 2. PROPOSALS IN GUIDELINES

### i Harmonisation of use of system charges for generators

To avoid distortions of competition, some harmonisation of the charges for access to networks of the generators, i.e. the 'G' charge is desirable. Harmonisation of G charges, rather than L charges, is considered to be more important since the output from production facilities and the location of them is thought to be more responsive to price signals. However it should be emphasized that the 'G' charge is not the only charge a generator pays; connection charges have to be taken into account when making the investment decisions. The European countries have also different practises according to whether a generator is responsible for paying the costs connected to production related network components. It should also be emphasized that the level of network charges is not the only determinant of the decisions to locate plants. Other non-network related cost factors, such as fuel transportation costs or availability of cooling water, might be more important.

- Deleted: connected to the transmission grid, ie
- Deleted: the most
- Deleted: location of
- Deleted: output from
- Deleted: This
- Deleted: say
- Deleted: .

Tariff structures and charging principles may vary widely from country to country but also within a country depending on voltage level and region. It is therefore proposed that G charges will be harmonised at transmission level and on the basis of the national average level of the G-charges. For each Member State, the average G charge will have to remain within the specified range, which should be transparently and non-discriminatory calculated for each country. A positive G charge can be important e.g. for the financing of the inter-TSO compensations especially in heavily exporting countries.

- Deleted: for access to networks to generators: "national average G". Member States will accordingly be able to have variations in charges for their internal regions ("national locational signals").
- Deleted: The possibility
- Deleted: of a
- Deleted: is
- Deleted: for example
- Deleted: the TSO contribution to
- Deleted: compensation fund by the generators, which might be particularly appropriate
- Deleted: . It
- Deleted: and in any case before end 2006

Within the Nordel, UK and Irish systems, interconnected by DC submarine cables to UCTE, the main continental system, different ranges for the 'national average G' may be applied and the ranges will be re-examined in the later stage.

The need for harmonisation of G-charges on other voltage levels and harmonisation of tariff structures should be investigated also in the later stage.

## ii European locational signals

Under the Regulation, all Member States will be required to participate in the inter-TSO compensation mechanism and to implement market based congestion management methods for the interconnectors. This will lead to a large increase in the impact of locational signals, especially short-term locational signals, at European level relating to the siting of generation and consumption.

Given the limited capacity of interconnection between different Member States, the countries with a general surplus of capacity over load will generally be low price areas due to e.g. lower production costs or insufficient interconnection capacities. Those with a deficit will be higher priced regions. With market based capacity allocation at interconnectors, this price difference will be made explicit. Any new generation in surplus regions will therefore face either a low price for energy in their domestic market or a high interconnector charge to sell in higher prices countries. This will provide a clear locational signal. Similarly, compulsory participation in the inter TSO compensation mechanism will ensure that Member States which host cross border flows are compensated for providing this service.

Charges covering costs of losses and other ancillary services can give short-term locational signals and application of these charges is important for achieving an efficient operation of the network. The need for eventual harmonisation in connection to these charges should be investigated in detail in the future.

At this stage it is not considered appropriate, in the sense of Article 4(2), to introduce through the harmonisation of G and L charges, locational signals at the European level. The main reason for this is the uncertainty how efficient and accurate these signals can be since there are so many other costs to consider when making an investment decisions, and to what extent giving such signals through the G/L-charge can distort short term signals. However, the situation needs to be closely monitored and the details for harmonised long term locational signals will be considered in the later stage.

Deleted: those

Deleted: home

Deleted: transmission

Deleted: suitably

Deleted: ¶  
Consequently, at

Deleted: ¶  
Given the existence of sufficient locational signals, all other charges relating to cross border exchanges must be removed, in accordance with Article 4(4).¶  
¶

## ANNEX: DRAFT GUIDELINES

### 1 Harmonisation

- 1.1. The value of the 'annual national average G' is annual total transmission tariff fees paid by generators divided by the total measured energy injected annually by generators to the transmission network. Annual average G shall exclude any fees paid by generators for physical assets required for the generators connection to the system (or the upgrade of the connection) as well as any fees paid by generators related to ancillary services or any specific network loss charges paid by generators
- 1.2. The value of the 'annual national average G' must be within a range of 0 to 0.5 €/MWh, with the exception of the cases in 1.3 to 1.5 below.
- 1.3. The value of the 'annual national average G' within the Nordel system, shall be within the range of 0.25 to 0.7 €/MWh.
- 1.4. The value of the 'annual national average G' within the GB system will be at maximum 2.5 €/MWh
- 1.5. The value of the 'annual national average G' within the Republic of Ireland and within Northern Ireland will be at maximum 2.5 €/MWh.

**Deleted:** The value of the 'annual national average G' is an arithmetic average of all the hourly tariffs of the year, including off-peak and peak-tariffs, and the different seasonal variations. When the tariff includes a 'capacity' fee, the 'annual national average G' has to be calculated for a generator assuming that it is injecting electricity during 5000 hours per year at its declared power capacity. A weighted average, based on generation, will be included in the 'annual national average G' in case of variations in charges within the internal regions ("national locational signals").

**Deleted:** the

**Deleted:** relating

**Deleted:** to the TSOs role in balancing the transmission system

**Inserted:** to the TSOs role in balancing the transmission system or any

**Deleted:** relating to capital and operation costs'

**Deleted:** (Finland, Norway, Sweden and Denmark) will be at maximum 0.85 €/ MWh

**Deleted:** [actual average G in GB]

**Deleted:** [actual average G in Irl]

**Deleted:** other charges relating, for example, to initial connection to the network, losses, and other ancillary services need not be harmonised

**Inserted:**

**Deleted:** contract

**Deleted:** submit

**Deleted:** the details of

**Deleted:** the

**Deleted:** of their TSOs to the Commission

**Deleted:** on

**Deleted:** 30

**Deleted:** November

**Deleted:** and on the occasion of any amendments to the tariff structure relevant to these guidelines

### 2 Removal of international supply transaction based charges

With the exception of charges resulting from market based congestion management methods, charges for access to networks applied to producers and consumers shall be applied regardless of the countries of destination and, origin, respectively, of the electricity, as specified in the underlying supply arrangement. This includes all import, export and transit fees.

### 3 Reporting

National regulators will report to the Commission how the TSOs charging structures will comply with the Guidelines by 28 February 2006. National Regulators shall provide the value of the annual national average G to the Commission by the end of July 2007. Afterwards only amendments to the charging structures and G-values shall be submitted to the Commission yearly by the end of July.